

2

10

1

11

3

4

Sofabaton X1S?	II Positioning the X1S-Hub		III Video tuto	
and Wi-Fi setup for X1S-Hub debase to your hub.			You can scan the QR watch the video tutc	
evice or activity to control. does not have an infrared e sent from the X1S-Hub.		IR blaster	https://sofabaton.com/video_tuto	
			Email: Service@eefebaten.com	
	 For open cabinets, position X1S-Hub on top of your cabinet, or on a large, open shelf that's unobstructed. IR signals sent from the hub will reflect off walls and other surfaces before reaching your devices. Direct line of sight is generally not required. If your device is placed in an inaccessible corner or cabinet, it is recommended that you use an IR blaster with the transmitter pointed at the device. 	 For closed cabinets, position the X1S-Hub inside the cabinet, under or beside your devices. IR signals sent from the hub will reflect off walls, cabinet interiors, and other surfaces before reaching your devices. Direct line of sight is generally not required. Plug the IR blaster into the back of the hub and position it on top of your cabinet, with the transmitter pointed at your television. 		
oogle Assistant	MI Specifications and Performance			
use of Amazon Alexa	Product name: X1S Smart Remote		1.Key Definitions fo	r X1S-Hub
Activity on or off. r watch video tutorials ts for Alexa and Google	X1S-Hub Input parameters: 5V/2A Input interface: USB Type-C Wi-Fi: IEEE 802.11 b/g/n, @2.4 GHz, WEP/WPA-PSK/W-	Global keys	Function Find the X1S-Remote	Action Click the but
ve a microphone to d you'll need to use smart speaker to control vities using the Sofaba-	PA2-PSK Bluetooth: BLE 5.0(Bluetooth LE) &Bluetooth 3.0 Infrared: 10 KHz ~ 100 KHz Material: PMMA X1S Remote	() () ()	Wi-Fi setup	Press and ho the button fo least three seconds
ccount linking in the me app. Activities on or off with n't control the device.	Battery type: Li-Polymer Battery capacity: 1050mAh Input interface: USB Type-C Input parameters: 5V/0.4A Charging time: About 3 hours		2.LED Indications	
a device, you can set it	Working time: About 45 days Material: PC	Global keys:	Status	L
		Off: Power off all Activities.	WLAN not connected	
	Package contents: 1 * X1S-Hub	Return: Return to the previous menu of the X1S -Remote	WLAN connected	Gree
	1* X1S-Remote	display.		0.0

1* X1S-Remote 1 * Charger 2 * Type-C cable 1 * Infrared Blaster with 1 TX

1 * Infrared Blaster with 2 TX 1 * User manual

Wheel: When the X1S-Remote screen is locked, click or scroll

to light it up. When the screen is lit, scroll up and down to switch menus, as well as click to confirm.

Non-global keys:

These keys have no default values and need to be defined on the device or while in Activity mode.

12

13

14

15

Abnormal status

Received a command

from App or

X1S-Remote

6

7



16

17

18